

1000 Watt Inverter with Charger



Max. Continuous Power	1000 watts
Peak Power	2000 watts
AC output voltage	110V or 120V or 220V or 230V or 240V AC
AC output frequency	50 or 60 +/-2 Hz
AC output waveform	Pure Sine Wave
DC input voltage	12V or 24V or 48V or 110V DC
voltage range	10.5~15.0V or 21.0~30.0V or 42.0~60VDC
No Load Current Draw	<0.5 amps(at 12V input)
LED Indicator	Input voltage level, output load level and status
Efficiency (Typ.)	>86%
Fuse (12V)	30A *2 (12V) / 15A *2(24V) / 10A *(48V)
Bat. Low Alarm	10.5V or 21.0V or 42.0V DC
Bat. Low Shutdown	10.0V or 20.0V or 40.0V DC
Over Load	Shut off output voltage, re-power on to recover
Over Voltage	15.5V or 31.0V or 62.0V DC
Cooling	Loading controlled cooling fan
Dimensions	311x265x93mm(LxWxH)
Weight	5.3Kgs



Price:
 Php P13,500.00
 USD \$270.00

- Warranty for solar charge controller and power inverter is 1 year
- Quotation Valid for two months only
- Allow 20 days of production and shipping time for large orders
- Local freight to be paid by buyer

www.sophilcor.com
sophilco@gmail.com

